



FLEXware Mounting Plates




Integration Enclosures and Hardware



Single MP Configuration for FLEXware 500



Dual MP Configuration for FLEXware 1000



Features:

- FLEXware MP is a one-piece, powder-coated aluminum mounting plate for FLEXware 500 and FLEXware 1000 enclosures
- Integrated stainless steel locating bolts make installation quick and easy by providing guides to line up enclosures and inverter/chargers
- FLEXware MP accommodates FLEXware 500 while two FLEXware MPs are utilized in FLEXware 1000 configuration

FLEXware Mounting Plates Specifications

07/2020

Model	FW-MP
Description	FLEXware system mounting plate
Shipping Weight (lb/kg)	14 / 6.4
Dimensions H x W x D (in/cm)	Unit: 20.3 x 46.3 x 0.8 / 51.6 x 117.6 x 2.1 Shipping: 1.15 x 22.9 x 48.4 / 2.9 x 58.2 x 123

Preliminary specifications are subject to change.

980-0064-01-00 REV A



Worldwide Corporate Offices

Headquarter Germany

Hansastraße 8
D-91126 Schwabach
Tel: +49 9122 79889 0
Fax: +49 9122 79889 21
Mail: info@alpha-outback-energy.com

Eastern Europe

ee@alpha-outback-energy.com

Middle East

me@alpha-outback-energy.com

France and Benelux

fbnl@alpha-outback-energy.com

Spain

spain@alpha-outback-energy.com

Russia

russia@alpha-outback-energy.com

Africa

africa@alpha-outback-energy.com

Alpha and Outback Energy GmbH reserves the right to make changes to the products and information contained in this document without notice. Copyright © 2020 Alpha and Outback Energy GmbH. All Rights reserved.

For more information please visit www.alpha-outback-energy.com